

取扱説明書 海外・日本国内用変圧器

特長

※軽量でコンパクトサイズ。
※サーマルプロテクタ内蔵と電流ヒューズ付きで安全安心設計。
※便利な2口コンセント。

使用方法

①ご使用前に必ず電圧切替スイッチが使用する国の電圧側になっていることをご確認ください。
スイッチは230V側にセットされていますので100V(日本)で使用する場合は切替えが必要となります。
※切替え方法: ドライバーで金具を外しスイッチを切替えてください。

CHANGE OVER SWITCH

↑ 100V
↓ 230V

固定金具

(例1)
220V・240Vの国で日本製品を使用する場合。
For using Japanese electrical product in countries with 220V-240V.

CHANGE OVER SWITCH

↑ 100V
↓ 230V

固定金具

(例2)
日本国内で220V・240Vの国の海外製品を使用する場合。
For using 220V・240V overseas electrical products in Japan.

コンセント形状

入力コンセント形状

出力コンセント形状

電流ヒューズ

※ヒューズが切れてしまった場合は、本体背面のヒューズボックスのcockをマイナスドライバーなどで左へ45°回転させ、中に入っているヒューズを交換してください。(別売: 6S 20A/250V スロータイプ Φ6.35×31.8mm)

(本体裏面図)

ヒューズボックス

使用できる国と使用できる電気製品

使用できる国や地域の電圧: 100V/220V-240V

使用できる電気製品: 本製品の定格容量(1500VA)以内の電気製品

TRAIT

※Light and Compact.
※Designed safely with the thermal protector and the current fuse.
※Convenient two item outlets.

OUTLET SHAPE

INPUT OUTLET SHAPE

OUTPUT OUTLET SHAPE

HOW TO USE

①Before using, you must check if the voltage changeover switch is at the right position which is same as voltage of the countries that you are using transformer. The voltage changeover switch is set at 230V, please turn to 100V if you use it in Japan.
②Switch method: To switch, remove the metal fittings with a screwdriver.
③Please plug transformer to the wall socket, if the shape of wall socket is different from type A, please buy adaptor separately.
④Please plug your electrical appliances to the output socket of this transformer. Please socket the plug match with the outlet. (Type A and C only)
⑤Please unplug this product power plug after use.

ATTENTION

※Please check the electrical consumption power (W) of your product before use. It must be within the maximum power (VA) limit of the transformer.
(Use in Japan Max1500VA, in other country Max1500VA.)
※Please must not change over the voltage switch during the application of the electrical appliances. This may cause malfunction and damage to your electrical appliances.
※For electrical socket of 15A spec, the transformer should be used at alone. Do not plug other electrical appliances to the same socket.
※Please do not use the transformer if there is damage in power cord or electrical plug or if you find the socket is loose after insertion of transformer's plug.
※Please do not damage the power cord, over bending, stretching, twisting, putting heavy things on top, cutting, processing or wrapping the power cord to the transformer body.
※The electrical plug of overseas electrical appliances the shape of wall sockets are all different.
If the shape of wall socket is different, please buy adaptor separately.
※When turning on heat-generated appliances such as illuminating products or motors, the initial current is 2 to 3 times more than the rated current.
Please check with the manufacturer of your electrical appliances.
※Please set to 80% of the maximum rated current capacity when continue using for more than an hour.
(Working temperature and loading condition can be varied. The figure indicated is just a reference.)
※When the temperature of inside of this product goes up abnormally, the protection instrument works automatically and the output doesn't go out.
In that case, please let the plug removed from the outlet and wait this product cooled. You can use it again.
※In Japan, there is a frequency region 60Hz and 50Hz region. Please note that you may if you disagree with the frequency of electrical products can not be used overseas.
※The painting of this product might come off, or might get scratched.
※Please do not immerse this transformer in water, or allow water to spill on it. This may cause damage in insulation or result in electrical shock.
※Do not take apart, repair or modify the transformer.
※Please avoid storage in high temperature and humidity place, must store in cool place with good air ventilation.
※This product cannot be functioned under low capacity condition such as in the hotel or in the home.
※If there is any smoke, abnormal smell or sound coming out from transformer, please unplug the transformer immediately because there may be danger of fire or electrical shock.
※If there is damage in home electrical appliances and wall socket, this transformer may also be damaged. Please pay attention.
※Please do not use with medical devices or machine that affect human's life.
※In the case of small capacity breaker, there is a possibility that breakers are actuated because a big temporary electric current flows when the power supply plug of the transformer is plugged into an outlet.
※Please backup all the necessary data, we are not accountable for any data loss when using this device.
※Natural disasters like lightning etc, wrong installation, self modification may cause accident, troubles or other damages.
We cannot guarantee our product under those situations.

OVERSEAS ELECTRIC CIRCUMSTANCES

※If washroom's socket is especially made for shaver of low current, please use other indoor sockets.
※For other indoor sockets, especially hotels, there is a type of socket especially for vacuum cleaner which can only conduct electricity when customers check out their room. If transformer cannot operate normally, please use other sockets.
※Beside the socket, if there is a switch, you must turn on the switch to allow electricity conduction.

CURRENT FUSE

※When the fuse cuts(optional: 6S 20A/250V slow type Φ6.35×31.8mm), please rotate the cock of the fuse box on the back of the main body left by 45° with a minus driver and exchange for new one.

AVAILABLE COUNTRY AND ELECTRIC PRODUCT

The countries regions that can use this transformer and their specified voltage: 100V/220V-240V

Available country: Japan / Britain / Germany / Italy / Singapore / Malaysia / China / Thailand and others.

Available electric products: The capacity of this product is good for electrical appliances with power less than (1500VA)

The example of electrical appliances that can used with this transformer: Television / Lap-top computer / digital-audio player / hair iron / electric toothbrush / digital camera / beard trimmer / video camera etc.

型 式

TTS-20C

定格仕様

入力定格

230V

100V

使用周波数

50/60Hz

50/60Hz

出力定格

AC100V
1500VA

AC230V
1500VA

本体サイズ

134W×110H×175D

重 量

6.0kg

電源コード長

2m

生産国

MADE IN CHINA

特 記 事 項

ガム

※本製品のデザイン、仕様等は予告なく変更する場合があります。予めご了承ください。
※レシートは必ず保管してください。万一の製品不良による返品の際に必要となります。
※本製品は日本の株式会社カシムラの企画・設計により中国で製造されたものです。
ENGINEERED BY KASHIMURA, JAPAN
※ゴミに出す時は市区町村の区分に従ってください。

保証書

型 式

TTS-20C

保証期間

お買い上げ日より1年

お買い上げ日

年 月 日

ご住所

お名前

電話番号

販売店名・印